



PART NO.	A	B	C	D	E
FFT-1	15.0	8.0	7.5	3.7	3.5
FFT-2	20.0	12.1	8.2	4.1	5.5
FFT-3	25.1	16.2	10.4	4.3	8.1
FFT-4	24.4	22.4	8.9	4.6	6.0
FFT-5	26.0	12.7	10.9	5.1	5.7
FFT-6	22.5	22.4	8.6	4.6	6.0
FFT-7	17.0	17.0	7.5	3.2	6.0
FFT-8	19.8	20.0	9.5	4.2	5.7
FFT-9	20.0	12.8	9.5	3.6	5.7
FFT-10	20.0	10.5	9.2	4.4	4.0
FFT-11	28.5	8.2	11.29	7.1	6.0